

udohow anahtarsız akıllı kapı kilidi için kart ile otel / proje kullanımı DH8014Y

DH8014-Y

RFID HOTEL DOOR LOCK

UDOHOW RF CARD DOOR LOCK /HOTEL LOCK requires no wiring,adopts the RF card of USA TEMIC company or RF card of PHILIPS company to perform control function and unlocking function, iscompletely independent and stand-alone, is controlled by programresident in the lock and activated by cards which are coded by issuing computer. Keycard options include TEMIC 5557 card and MIFARE 1K or 4K card, which are compatible with RF andMIFARE Energy SAV, All of these make installation and maintenance becomes simple and easy.



▶ Product Pictures:



Uygulanabilir kart: Mifare kartı, Temic kartı ve kimlik kartı

Güç kaynağı: DC6V, 4PCS Standart AA Alkalin Pil

Pil Ömrü: kullanım durumuna bağlı olarak yaklaşık 1 yıl.

Düşük voltaj uyarısı: Voltaj 4.8v'den az, 3 ses ve kırmızı LED ışığı olacak. Pil değiştirilmeden önce kilidin kilidi hala 50 kereden fazla açılabilir.

Kart çalışmasının güvenilirliği: Kartın 1000 kez sürekli çalışması için kaza olmaz

Acil kilit açma: Sürgü acil durumda çalışıyor olsa bile, kapının kilidi Master kart VEYA Mekanik anahtar ile açılabilir.

Montaj talebi: Kapıya, kapı kalınlığı 35 mm ile 55 mm arasında olacak şekilde monte edilmelidir. Kapı yüzeyi dekore edilmişse, dekorasyon kenarı ile kapı kenarı arasındaki mesafe 95 mm'nin üzerinde olmalıdır.